




















# SPC Smartbox - Z-Wave Devices Compatibility Guide











V1.0

This compatibility guide should be seen as guidance and Lundix IT cannot guarantee that all information is correct since the manufacturers regularly release new software that could cause incompatibility. The devices are only tested with basic configuration settings.

The SPC SmartBox Z-Wave Device Database is based on Z-Wave Alliance certified devices. Even if the device is missed in the database the device should be possible to operate (but you need to use the generic configuration tool).

-  Fully compatible with latest tested software.
-  Partly compatible with latest tested software.
-  Incompatible with latest tested software.

|   | Manufacturer | Device Type           | Product     | Remark   |
|---|--------------|-----------------------|-------------|--|
|  | Aeon Labs    | Multisensor           | ZW100-C     | Some configuration needed to get report from all sensor types.   |
|  | Aeon Labs    | Power Switch          | ZW078-C     | Set parameter 80 to 2 to get report on changes.  |
|  | Aeon Labs    | Power Switch          | ZW139       | Missed in Device database  |
|  | Aeon Labs    | Dimmer                | ZW111-C     | Set parameter 80 to 3 to get report on changes.  |
|  | Danfoss      | Temperature Sensor    | 014G0160    | Only reading of temperature supported. Thermostat features not supported.  |
|  | Everspring   | Dimmer                | AD147-2     | Select AD147-6 in Device database. Report time configurable. Default and minimum 3 seconds.  |
|  | Everspring   | Power Switch          | AN180-2     | Select AD180-6 in Device database. Report time configurable. Default 3 seconds.  |
|  | Fibaro       | Dimmer                | FGD-212     | The device has three endpoints. Use endpoint 1 for control of dimmer.  |
|  | Fibaro       | Flood Sensor          | FGFS-101    | -  |
|  | Fibaro       | Power Switch (double) | FGS-223     | The device has three endpoints. Use endpoint 1 for control of switch 1 and endpoint 2 for control of switch 2..  |
|  | Fibaro       | Power Switch          | FGWPE/F-101 | Configuration descriptions missed in Device database, but you can still use the generic configuration tool.  |
|  | Fibaro       | Power Switch          | FGWPE/F-102 | -  |
|  | Fibaro       | Universalsensor       |             | Missed in Device database. Only support for the temperature sensors.   |
|  | MCO          | Power Switch          | MH-S412     | The device has three endpoints. Use endpoint 1 for control of button 1 and endpoint 2 for control of button 2. Endpoint 0 shouldn't be used.<br>Set association group 3 to Device_1:0 (Controller) to get report on state changes when you use the physical buttons. |
|  | NodOn        | Power Switch          | MSP-3-1-X1  | -  |
|  | NodOn        | Soft Remote           | CRC360X     | Command classes not supported  |

|   |             |                     |           |  |
|---|-------------|---------------------|-----------|--|
|  | Philio Tech | Multisensor         | PST02-1C  | -  |
|  | Philio Tech | Power Switch        | PAN11-1B  | After inclusion the device is show up as PAN11-1A. You have to manually change product type to PAN11-1B.   |
|  | Popp        | Water Valve Control | Flow Stop | -  |
|  | Schneider   | Dimmer              | 1700742   | Controllable but no report on changes  |
|  | Schneider   | Power Switch        | 1700851   | -  |
|  | SwiidInter  | Power Switch (Cord) | SW-ZCS-1  | -  |
|  | TKB Home    | Dimmer              | TZ67G     | Report time on changes is 3 seconds. Configuration descriptions missed in Device database, but you can still use the generic configuration tool. |
|  | TKB Home    | Dimmer              | TZ55D     | Missed in Device database.   |
|  | Qubino      | Power Switch        | ZMNHN     | -  |
|  | Qubino      | Dimmer              | ZMNHDD1   | External temperature sensor not tested   |